



# AKT1

## 200m2 TV/Music Lounge Hearing Loop Kit



### Overview

Includes a PDA200E hearingloop amplifier, AMP handheld microphone, APS SCART to double phono lead, APXM outreach plate, APL outreach plate, AL5 lead and 2 x 6m Belden cable.

Ideal for creating a high quality induction loop system for a TV or Music lounge.

Wall-mountable PDA200E amplifier capable of driving a perimeter loop of up to 200m2.

Internal drive, level and metal compensation controls.

Two balanced / unbalanced line level inputs.

One microphone input with 12V phantom power for electret microphones.

Full compatibility with the Outreach plate audio input extension system.

Fully compliant with BS EN 60118-4 when correctly installed.

Loop cable not included-use our LOOP2W1mm2 cable or download our AFILS loop calculator from our Software & Apps page for more precise recommendations.

### Technical Specifications

<b>Type</b>	Wall mounting. Requires fixed Mains wiring.
<b>Coverage</b>	200m2 approx.
<b>Mains supply</b>	230V 50/60Hz.
<b>Auxiliary inputs</b>	1 Microphone and 2 x Line/Outreach screw connectors (on PDA200E).
<b>Indicators</b>	Input level; loop current meter (peak 3, 2, 1); compression; power on.
<b>Controls</b>	Input level; loop drive, metal compensation.
<b>Product dimensions (mm)</b>	W 271 x H 200 x D 77mm (amplifier only).
<b>Construction &amp; finish</b>	White painted steel (PDA200E); plastic accessories.
<b>IP Rating</b>	IP20.
<b>Weight</b>	2.9 kg (amplifier only).
<b>Operating conditions/temperature</b>	-5°C to +40°C. Max relative humidity: 95%.
<b>Kit contents</b>	PDA200E hearing loop amplifier; AMP handheld microphone, APS SCART lead, APXM XLR mic. level connector plate, APL dual phono line level connector plate, AL5 lead; 2 x 6m Belden cable; Loop Fitted sticker. Loop cable IS NOT included.