



BOSCH
Invented for life

LBB 1997/00 Plena Voice Alarm System Remote Control Extension



- ▶ Remote control of the voice alarm routers
- ▶ EMG and background (BGM) zone selections
- ▶ EMG state and fault indicators
- ▶ One extension per router
- ▶ Power supply from the remote control panel (kit)

The Plena voice alarm remote control panels allow the system to be controlled remotely from one or two remote locations. There are five models available:

- The fireman's panel, which has oversized, illuminated controls and an all-call function
- The main RC unit, which duplicates the front panel of the Voice Alarm Controller
- The RC extension, which duplicates the front panel of the router
- The main RC kit
- The RC extension kit

The kits are a functional match to the remote control and the RC extension, with connectors on the front panel instead of controls and indicators.

Functions

The extension duplicates the Plena LBB 1992/00 Voice Alarm Router front panel. One extension is needed per router, but not all routers need to have a remote control.

An LED meter shows the presence and level of the calls that are running in the system. The fault indicators show detailed information of any faults present in the system. The unit connects to the Plena Voice Alarm System via standard shielded CAT 5 cable. The included rack mounting brackets can also mount the unit on a wall with spacing for cables at

the back, as well as to a horizontal surface above or below the unit.

One or more extensions need to be connected to a voice alarm RC or voice alarm RC kit.

Certifications and Approvals

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1
EVAC (TÜV certified)	acc. to IEC 60849

Installation/Configuration Notes



LBB 1997/00 rear view

Parts Included

Quantity	Component
1	LBB 1997/00 Plena Voice Alarm System Remote Control Extension
1	Set of 19" mounting brackets
1	1 m CAT 5 cable

Technical Specifications

Electrical*

Power supply

Voltage	24 VDC, -10% to +20%
Current typical	50 mA
Current max (indicator test)	200 mA (indicator test)
Relay contacts	30 V, 1 A

* Technical performance data according to IEC 60268-3

Mechanical

Dimensions (H x W x D)	88 x 430 x 90 mm (19 in wide, 2U high)
Weight	Approx. 2 kg
Mounting	Stand-alone, 19" rack
Color	Charcoal

Environmental

Operating temperature	-10 °C to +55 °C (14 °F to +131 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Ordering Information

LBB 1997/00 Plena Voice Alarm System Remote Control Extension LBB 1997/00
six-zone voice alarm router remote control

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by