

# CGN99 C

CARDIOD CONDENSER GOOSENECK MICROPHONES

[Features](#) [Specs](#) [Downloads](#)

## AN EASY JOB

*for use in houses of worship, conference rooms and theaters*

The CGN99 C/S and CGN99 C/L, part of the DAC Series, are condenser gooseneck microphones with a cardioid polar pattern. They are specially designed for inexperienced speakers who talk into the microphone from widely varying angles.

The rugged gooseneck is available in two different lengths (C/S: 30cm (12in); C/L: 50cm (20in) and ideal for fixed and mobile installations. CGN99 C/S and CGN99 C/L come with an integrated XLR phantom power adapter with 250Hz bass rolloff. The phantom power adapter connects to any standard mixer input with 9V to 52V power supply.

### Compact solution

for plug and play

### Cardioid polar pattern

eliminates noise from the rear

### Two different gooseneck lengths

30cm (C)




## TECHNICAL SPECIFICATION

<b>General</b>	Audio frequency bandwidth	70 to 18000 Hz
	Equivalent Noise Level	21 dB-A
	Signal to Noise	73 dB-A
	Bass Cut Filter	250 Hz
	Electrical Impedance	600 Ohms
	Recommended Load Impedance	2000 Ohms

### Polar Patterns

Cardioid



<b>Powering Interface</b>	Voltage	9 to 52 V
	Current	3 mA

<b>Audio Output</b>	Type	Balanced XLR
	Gender	Male
	Contacts	3-pin

<b>Design</b>	Finish	matte black
---------------	--------	-------------

<b>Dimensions / Weight</b>	Height	380 mm
----------------------------	--------	--------