


## **BM 3804FM** FIREMEN EMERGENCY MICROPHONE CONSOLE






## **BM 3804FM** FIREMEN EMERGENCY MICROPHONE CONSOLE

Line Art 2D







	TECHNICAL SPECIFICATIONS	
Microphone specifications	Туре	Dynamic
	Directivity	Omnidirectional
	Sensitivity	-70 dB
	Frequency Response (-3dB) Output impedance (ohm)	300 Hz ÷ 6000 kHz 500.00 ohm
Console specifications		
console specifications	Console Type Working with	Emergency DXT 3000
	General call	Yes
	Selective call	Yes
	Preamplified	Yes
	LED indicators	Yes
Power requirement	Operating voltage	24.00V ~ Hz
Connections	Connectors	RJ45
	Cable	J-Type fire-rated
	Daisy-chain	Yes
	Max number in daisy-chain	4
	Interlock	Yes
Functionalities	Priority	Yes
	Chime tone generator	Yes
Accessories	Cable included	Yes
	Cable length (m)	5
Standard compliance	Safety agency	CE compliant
	EN54-16 certified	Yes
	CPR number	0068-CPR-007/2015
Physical specifications	Cabinet/Case Material	Metal
	Color	Red - RAL 3000
Size	Height	360 mm / 14.17 inches
	Width	360 mm / 14.17 inches
	Depth	129 mm / 5.08 inches
	Weight	6.9 kg / 15.21 lbs



## BM 3804FM

FIREMEN EMERGENCY MICROPHONE CONSOLE

## ACCESSORIES

Cables Electronics CJ 428CAT AC AD2405 123990478024530016449143800228024530007027