# BExL25 Explosion Proof PA Loudspeakers 25W



# The flameproof BExL25 PA loudspeakers are suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx, ATEX, Ex EAC and INMETRO standards.

119dB sound level output - 25W rated.

The BEx range features enclosures manufactured from corrosion proof, marine grade copper free LM6 aluminium with chromate and powder coat finish.

An independent test report is available on request, or online, detailing the leading performance of the BEx loudspeaker range.

### **Features**

- ٠ Marine grade, corrosion proof, LM6 aluminium enclosure.
- Ingress protection IP66/67
- Stainless steel fixings
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Very large termination area.
- Ratchet adjustable stainless steel 'U' bracket.
- 100V and 70V line versions.
- 8 Ohm and 16 Ohm low impedance versions.
- Multiple tappings from 25W to 2W.
- Wide frequency response and angle of dispersion. •

### **Approvals**

- IECEX KEM 10.0003X
- ATEX KEMA 99ATEX6312X
- TR-CU Ex EAC certificate: RU C-GB.HA65.B.01252\_21
- INMETRO certificate: 10-IEx-0009 •

### Coding

- II 2G Ex db IIB T4 Ta -50° to +70°C
- II 2G Ex db IIC T4 Ta -50° to +55°C
- II 2D Ex tb IIIC T100°C Db Ta -50°C to +55°C
- II 2D Ex tb IIIC T115°C Db Ta -50°C to +70°C


















### Specification

## Part Codes

epeenneation		1 410 00400		
SPL:	105dB +/-3dB @ 1w @ 1m (Pink) 110dB +/-3dB @ 1w @ 1m (Sweeping tone freq.) 119dB +/-3dB @ 25w @ 1m (Rated) 123dB(A) @ 1m (max. tone output)	<b>Version:</b> Product type:	Part code: BExL25	Explosion proof PA Loudspeaker
		Туре:	DF	Ex d, Flare re-entrant horn
Rated power:	25 Watts RMS	Input:	V100	100V Line Transformer
70v line tappings:	25w / 12.5w / 6w / 2w tappings (z=196 Ohms / 392 Ohms / 816.67 Ohms / 2.45k Ohms)		V070 R016 R008	70V Line Transformer 16 Ohm Low Impedance 8 Ohm Low Impedance
100v line tappings	: 25w / 12.5w / 6w / 2w tappings (z=400 Ohms / 800 Ohms / 1.67k Ohms / 5k Ohms)	Cable Entry Type: [e]	A B C D E F G	$2 \times M20x1.5mm$ $2 \times 1/2'' NPT - adaptors$ $2 \times 3/4'' NPT - adaptors$ $2 \times M25x1.5mm - adaptors$ $1 \times 1/2'' NPT - adaptor$ $1 \times 3/4'' NPT - adaptor$ $1 \times M25x1.5mm - adaptor$
Low impedence:	8 Ohm or 16 Ohm			
Dispersion:	130° @ 1kHz & 32° @ 4kHz			
Frequency range:	300Hz to 8000 Hz	Adaptor/Stopping plug material: [m]	B	Brass Nickel Plated Stainless Steel
DC Line monitoring:	2.2µF Capacitor (Transformer) 470µF Capacitor (Impedance)			
Ingress protection:	IP66/67	Bracket matl & tag: [s]	: 1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag
Enclosure matl:	Marine grade copper free LM6 Aluminium			
Enclosure finish:	Chromate & powder coated finish – anti-corrosion.			
Colour:	RAL 3000 Red Grey RAL 7038 Special – available on request	Product version: [v	]A1	Default – IECEx, ATEX, Ex EAC & INMETRO
		Enclosure colour: [x]	R G S	Red RAL3000 Grey RAL7038 Special – contact E2S
BExL25 flare:	High impact UL94 VO & 5VA FR ABS			
Cable entries:	Dual M20 ISO (one stopping plug inc)	Accessories:	SP65-0001-A4 SP65-0003-A4	Pole Mount Bracket Kit 2'' St/St A4 (316) Sunshade – St/St A4 (316)
Terminals:	0.5 - 2.5mm² (20-14 AWG)			
Relative humidity:	95% – Additional tropicalisation is recommended for applications where both high relative humidity and high ambient temperatures exist			
Weight:	70/100V line: 3.95kg/8.69lbs			

Low imp.: 3.56kg/7.83lbs

### E2S Warning Signals sales@e2s.com www.e2s.com

No lability is accepted for any consequence of the use of this document. The technical specification of this unit is subject to change without notice due to our policy of continual product development. All dimensions are approximate. This unit is sold subject to our standard conditions of sale, a copy of which is available on request.

17 Apr 2022